

LSVIM01 Vibration Interface module

LS communication Vibration pressure variation , Combustor vibration input , FFT analysis

■ Summary



*Vibration interface module input / output

Terminal block input / output unit

- Analog input (1 to 5 V) : 8

Panel I/O connector

- Auxiliary input(Analog) (1 to 5 V) : 2

- Digital output (Open collector) : 2

- Serial communication : 2

*USB connector (For maintenance)

- For maintenance communication mini-B : 1

*Indicator

- Display LED (RUN / STS / NSA / NSB) : 4

- General purpose display LED : 16

*Module operating ambient temperature range : -5 to 60°C

■ Overview Specifications

ITEM	SPECIFICATION
Analog input	8 1 to 5 V
Auxiliary input(Analog)(Panel I/O)	2 1 to 5 V
Digital output(Panel I/O)	2 DC 30 V
Serial communication	2 RS232C level
USB connector(For maintenance)	1 For maintenance communication mini-B
Self-diagnostic functions	Watchdog timer, MCU communication monitoring, Flash access monitoring, Clock monitor, Power-supply voltage(Low / High), CRC check
IDOL Implementation	Possible
Indicator	Display LED × 4: Run / Status / Network status A / Network status B Channel State LED × 16: Ch 1 to Ch 16 Arbitrarily set by internal logic
Dielectric strength	AC 500V Analog input terminal (Terminal block) - PE AC 500V Analog input terminal (Panel I/O) - PE AC 500V Digital output terminal (Panel I/O) - PE AC 500V RS232C Serial communication (Panel I/O) - PE
Environmental conditions	Ambient temperature (Operating / Storage) -5 to 60°C Ambient humidity (Operating / Storage) 0 to 95% RH (No condensation)
Operating power supply	DC 24 V ±20% Dual power reception (The voltage supplied from the backplane)
Shock / Vibration	15 G 11 ms / 3.5 mm @5 to 8.4 Hz, 1 G @8.4 to 150 Hz
Dimensions	62 mm (D) x 94 mm (H) x 46 mm (W) (Except projection)

LSVIM01 Vibration Interface module

LS communication Vibration pressure variation , Combustor vibration input , FFT analysis

■ Specifications

ITEM		SPECIFICATION	
Terminal block	Analog input	Number of channels	8 (Channel Individual Isolation)
		Input range	1 to 5 V
		Signal filter	Cutoff frequency 20 kHz (Input frequency characteristics ± 0.2 dB @ DC to 10 kHz)
		Input impedance	More than 100 k Ω
		Input frequency range	0 to 10 kHz
Panel I/O	Auxiliary input(Analog)	Number of channels	2 (Common)
		Input range	1 to 5 V / 12 bit
		Input impedance	More than 100 k Ω
	Digital output	Number of channels	2 (Common)
		Applied maximum voltage	DC 30 V
		Maximum load current	0.1 A
		Leakage current when OFF	0.1 mA or less
	Serial communication	Number of channels	2 (Common)
		Interface	RS232C level
		Maximum communication speed	115200 bps
USB connector(For maintenance)		1 (For maintenance communication mini-B)	
Calculation cycle usable in NPS		More than 50 ms	
Dielectric strength		AC 500 V Analog input terminal (Terminal block) - PE AC 500 V Analog input terminal (Panel I/O) - PE AC 500 V Digital output terminal (Panel I/O) - PE AC 500 V RS232C Serial communication (Panel I/O) - PE	
Self-diagnostic functions		Watchdog timer MCU communication monitoring Flash access monitoring Clock monitor Power-supply voltage (Low / High) CRC check	
Protective function		Overvoltage protection Overcurrent protection	
Indicator		- Display LED (RUN / STS /NSA / NSB) - Channel State LED (Arbitrarily set by internal logic)	
Current consumption		179 mA	
Weight		0.14 kg	
Dimensions		62 mm (D) x 94 mm (H) x 46 mm (W) (Except projection)	
Insulation method		Analog input Analog input terminal (Terminal block): Transformer insulation Analog input terminal (Panel I/O): Digital Isolator Isolation Digital output terminal (Panel I/O): Photocoupler insulation RS232C Serial communication (Panel I/O): Digital Isolator Isolation	
Hot swap		Possible	
Power supply		DC 24 V $\pm 20\%$ (The voltage supplied from the backplane)	
Environmental conditions	Module ambient temperature	(Operating / Storage) -5 to 60°C	
	Module ambient humidity	(Operating / Storage) 0 to 95% RH (No condensation)	
Vibration		3.5 mm @ 5 to 8.4 Hz 1 G @ 8.4 to 150 Hz	
Shock		15 G 11 ms	
Standard/Directive		EN 61131-2:2007, RoHS	

About compliant module type


For compliant modules of this product, please refer to "Compliant backplane list (CGS-S9901-E-XX)".

For compliant modules of this product, please refer to "Compliant accessory connector list (CGS-S9902-E-XX)".

LSVIM01 Vibration Interface module

LS communication Vibration pressure variation, Combustor vibration input, FFT analysis

Block diagram



P/S	: Power supply	MCU	: Micro control unit
SH2A	: Renesas SH-2A micro processor	FPGA	: Field programmable gate array
CLK	: Clock generation circuit	LED	: Light emitting diode
ISO	: Digital isolator	ADC	: Analog digital converter
DAC	: Digital analog converter	Flash	: Flash ROM
LVDS	: Low Voltage Differential Signaling	BP	: Backplane
PWM	: Pulse width modulation	DAC	: Digital analog converter
AMP	: Amplifier	AI	: Analog Input
P/C	: Photo Coupler	AO	: Analog Output
N.C	: No Connection	DO	: Digital Output
	: Fuse		: Diode

When using, please read the instruction manual attached to the product carefully and use it properly.

This catalog may not be distributed or reproduced in whole or in part without permission.

Please be aware that due to product improvements and modifications, the product description in this catalog may differ in certain respects from the actual product.

DIASYS Netmation/DIASYS Netmation4S is a registered trademark of Mitsubishi Heavy Industries, Ltd.

The service names and product names of other companies described in this catalog are the trademarks or registered trademarks of each company.